



CUSTOMER NO. 2

JCO2 Rec'd PCT/PTC 10 JUN 2005 PCT

Docket No.: 47253-00053USPX
(PATENT)

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Patent Application of:
Andreas Cedergren et al.

Application No.: 10/523987

Confirmation No.: N/A

Filed: February 9, 2005

Art Unit: N/A

For: RECEIVER AND METHOD FOR DECODING
OF TRUNCATED DATA

Examiner: Not Yet Assigned

CLAIM FOR PRIORITY

Commissioner for Patents
P.O. Box 1450
Alexandria, VA 22313-1450

I hereby certify that this correspondence is being deposited with the U.S. Postal Service with sufficient postage as First Class Mail, in an envelope addressed to: Commissioner for Patents, P.O. Box 1450, Alexandria, VA 22313-1450, on the date shown below.

Dated: 06-06-05

Signature:

(Margo Barbarash)

Dear Sir:

Applicant hereby claims priority under 35 U.S.C. 119 based on the following prior foreign application filed in the following foreign country on the date indicated:

Country	Application No.	Date
European Patent Office	02388051.1	August 14, 2002

Dated:

June 6, 2005

Respectfully submitted,

By

Ross T. Robinson

Registration No.: 47,031

JENKENS & GILCHRIST, A PROFESSIONAL
CORPORATION

1445 Ross Avenue, Suite 3200

Dallas, Texas 75202

(214) 855-4500

Attorneys For Applicant



Europäisches
Patentamt

European
Patent Office

Office européen
des brevets

REC'D 10 OCT 2003

WIPO

PCT

Bescheinigung

Certificate

Attestation

Die angehefteten Unterla-
gen stimmen mit der
ursprünglich eingereichten
Fassung der auf dem näch-
sten Blatt bezeichneten
europäischen Patentanmel-
dung überein.

The attached documents
are exact copies of the
European patent application
described on the following
page, as originally filed.

Les documents fixés à
cette attestation sont
conformes à la version
initialement déposée de
la demande de brevet
européen spécifiée à la
page suivante.

Patentanmeldung Nr. Patent application No. Demande de brevet n°

02388051.1

**PRIORITY
DOCUMENT**
SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH RULE 17.1(a) OR (b)

Der Präsident des Europäischen Patentamts;
Im Auftrag

For the President of the European Patent Office

Le Président de l'Office européen des brevets
p.o.

R C van Dijk

BEST AVAILABLE COPY



Anmeldung Nr:
Application no.: 02388051.1
Demande no:

Anmeldetag:
Date of filing: 14.08.02
Date de dépôt:

Anmelder/Applicant(s)/Demandeur(s):

Telefonaktiebolaget L M Ericsson (Publ)

126 25 Stockholm
SUEDE

Bezeichnung der Erfindung/Title of the invention/Titre de l'invention:
(Falls die Bezeichnung der Erfindung nicht angegeben ist, siehe Beschreibung.
If no title is shown please refer to the description.
Si aucun titre n'est indiqué se referer à la description.)

Selecting a rounded estimate in a receiver of coded digital data symbols

In Anspruch genommene Priorität(en) / Priority(ies) claimed /Priorité(s)
revendiquée(s)
Staat/Tag/Aktenzeichen/State/Date/File no./Pays/Date/Numéro de dépôt:

Internationale Patentklassifikation/International Patent Classification/
Classification internationale des brevets:

H04L1/00

Am Anmeldetag benannte Vertragstaaten/Contracting states designated at date of
filing/Etats contractants désignées lors du dépôt:

AT BE BG CH CY CZ DE DK EE ES FI FR GB GR IE IT LI LU MC NL PT SE SK TR

Selecting a rounded estimate in a receiver of coded digital data symbols

5 Technical Field of the Invention

The invention relates to a method of receiving coded digital data symbols sent from a transmitter through a transmission channel of a communications network, the method comprising the steps of calculating an estimate of a sent data symbol, said estimate being represented by a first number of bits;
10 selecting from said calculated estimate a second number of bits, said second number being lower than said first number, to achieve a rounded estimate being represented by said second number of bits; and decoding the rounded estimate to achieve a decoded data symbol. The invention further relates to a receiver for receiving coded digital data symbols sent from a transmitter
15 through a transmission channel of a communications network.

Description of Related Art

Terminals for use with such communications networks are normally limited in size and computational resources. One result of this limitation is that there is
20 only a limited bit width to represent data values in a terminal. Therefore, it will often be necessary to truncate or round data values before they can be handled in the terminal. In order to utilize the available bit width optimally, data values to be processed may be scaled by multiplying them with a scaling factor before they are truncated.

25 One example of data needing to be limited in bit width is found in the receiver of the terminal. The received signal is here represented as a digital data value having one limited bit width in two-complement notation in both the real and the imaginary parts. The received signal is then multiplied by the conjugate value of a channel estimate computed in the receiver to obtain an estimate of the sent coded data symbol. The conjugate value of a channel estimate also has a limited bit width in two-complement notation in both the real
30 and the imaginary parts, which may be equal to or different from that of the

received signal. When the two values are multiplied the resulting estimate will have a bit width that is equal to the sum of the two other bit widths. However, the bit width available for the processing of this estimate will also be limited and probably smaller than the sum of the two other bit widths.

5

Therefore, the bit width has to be reduced before the estimate is further processed, and a scaling factor may have to be selected in order to utilize the available bit width optimally. It is known to find a scaling factor by means of an optimisation algorithm that computes one fixed factor intended to be optimal in the current situation. However, since the signal level in the receiver typically changes very rapidly, a fixed factor will not be optimal. Adaptive algorithms that constantly updates the scaling factor based on the input signals are also known. Although these adaptive algorithms may be able to provide optimal scaling factors in most situations, they are quite complex and require considerable computational resources, and as mentioned before such resources are rarely available in the terminals in question here. Although reference is here made to a scaling factor and truncation, the same problem exists for other rounding methods as well.

10

15

20

Therefore, it is an object of the invention to provide a method of the above-mentioned type which can provide an optimal rounded estimate in most situations, and which can be performed with the limited computational resources of a terminal of the type described above.

25 Summary

According to the invention the object is achieved in that the method further comprises the steps of receiving from said network a target value for a block error rate of the transmission channel; and selecting said second number of bits in dependence on said target block error rate value.

30

Many networks provide information on such a target value, which should be used by the receiver, and by selecting a rounded estimate based on this target value, a simple method, which requires much less complexity than the

- known adaptive algorithms, is achieved. The estimated coded data symbols, of which the bit width is limited, are used as the input to a channel decoder, and the performance of this decoder changes with the selected rounded estimate, e.g. in the form of a scaling factor. For a given signal-to-interference
- 5 ratio the obtained block error rate depends on the scaling factor. When the target value for the block error rate is known, it is thus simple to select the scaling factor which is known to provide the best results in the range around this target value.
- 10 Although other rounding methods may be used, in one embodiment the step of selecting said second number of bits comprises the steps of multiplying said estimate by a scaling factor; and truncating a number of bits from said multiplied estimate.
- 15 In an expedient embodiment the scaling factor has the form 2^n , where n is an integer. The use of this scaling factor corresponds to shifting the bit values n bits to the left, and a scaling is achieved which requires almost no computational resources.
- 20 When the method further comprises the step of selecting said scaling factor from a stored table comprising corresponding values of said target block error rate and said scaling factor, it is just to select from the table the scaling factor corresponding to the received target value.
- 25 When said target block error rate value is the target BLER value defined in the technical specifications of 3GPP (3rd Generation Partnership Project), a method which is appropriate in terminals according to these specifications is achieved.
- 30 As mentioned, the invention also relates to a receiver for receiving coded digital data symbols sent from a transmitter through a transmission channel of a communications network, the receiver being arranged to calculate an estimate of a sent data symbol, said estimate being represented by a first

number of bits; select from said calculated estimate a second number of bits, said second number being lower than said first number, to achieve a rounded estimate being represented by said second number of bits; and decode the rounded estimate to achieve a decoded data symbol. When the receiver is
5 further arranged to receive from said network a target value for a block error rate of the transmission channel; and select said second number of bits in dependence on said target block error rate value, a receiver which can provide an optimal rounded estimate in most situations, and which can calculate the rounded estimate with the limited computational resources of a terminal
10 of the type described above, is achieved.

Although the receiver may use other rounding methods, in one embodiment the receiver is further arranged to select said second number of bits by multiplying said estimate by a scaling factor; and truncating a number of bits from
15 said multiplied estimate.

In an expedient embodiment the scaling factor has the form 2^n , where n is an integer. The use of this scaling factor corresponds to shifting the bit values n bits to the left, and a scaling is achieved which requires almost no computational resources.
20

When the receiver comprises a stored table comprising corresponding values of said target block error rate and said scaling factor, from which table said scaling factor can be selected, it is just to select from the table the scaling
25 factor corresponding to the received target value.

When said target block error rate value is the target BLER value defined in the technical specifications of 3GPP (3rd Generation Partnership Project), a receiver which is appropriate in terminals according to these specifications is
30 achieved.

Brief Description of the Drawings

The invention will now be described more fully below with reference to the drawings, in which

5 figure 1 shows a receiver circuit in which the invention may be used,

figure 2 shows how an estimate having 16 bits may be truncated so that the eight most significant bits remain,

10 figure 3 shows the situation of figure 2, when the estimate has a number of leading zeros,

figure 4 shows a situation in which the leading zeros are not included in the selected bits,

15

figure 5 shows how the estimate may be multiplied by a scaling factor before truncation,

20 figure 6 shows the circuit of figure 1 modified with a scaling circuit and a truncation circuit,

figure 7 shows the performance of a decoder measured as an achieved block error rate (BLER) as a function of the signal-to-interference ratio (SIR) of the received radio signal for two different scaling factors,

25

figure 8 shows a table corresponding to figure 7 for selection of the scaling factor,

30 figure 9 shows the performance of a decoder measured as an achieved block error rate (BLER) as a function of the signal-to-interference ratio (SIR) of the received radio signal for three different scaling factors, and

figure 10 shows a table corresponding to figure 9 for selection of the scaling factor.

Detailed Description of Embodiments

- 5 Figure 1 shows an example of a receiver circuit 1 in which the invention can be used. The receiver circuit 1 is here a part of a terminal, e.g. a mobile telephone, for use in a communications system according to the 3GPP UMTS standard (3rd Generation Partnership Project - Universal Mobile Telecommunications System). The receiver circuit could also be located in e.g. a base station corresponding to uplink transmission.

A radio signal representing coded data symbols sent from a corresponding transmitter is received through an antenna 2 and down-converted to a base-band signal in a front-end receiver block 3. This block further includes a
 15 number of other functions, such as amplification, automatic gain control, analog-to-digital conversion, despreading and a RAKE combiner, but since these functions are not relevant to the present invention, they are not described in further detail here.

- 20 The output signal from the front-end receiver block 3 is a signal r , which can be described as $r = hx + n$, where h represents the transmission channel, x is the sent coded data symbol, and n represents noise. All parameters are complex values. The signal r is represented as a digital value in the circuit by a number of bits, e.g. a bits, in two-compliment notation in the real as well as
 25 the imaginary part.

A channel estimator 4 computes a channel estimate \hat{h} from the received signal r . This estimate is also represented as a digital value in the circuit by a number of bits, e.g. b bits, in two-compliment notation in the real as well as
 30 the imaginary part. The conjugate function 5 calculates the complex conjugate of the channel estimate \hat{h} , and an estimate y of the sent coded data symbol x is then achieved by multiplying the received signal r by the conjugate of the channel estimate \hat{h} , i.e. $y = \hat{h}^* r$.

The estimate y would now be represented as a digital value by $a + b$ bits in two-compliment notation in the real as well as the imaginary part, but typically the computational resources are not sufficient to handle values with so many bits, and therefore some of the bits have to be truncated so that the estimate y is represented by e.g. c bits, where $c < a + b$, before the estimate is further processed in a channel decoder 6.

Figure 2 illustrates an example, where the received signal r and the conjugate \hat{h}^* of the channel estimate \hat{h} are both represented by eight bits, i.e. $a = b = 8$. The estimate y will then be represented by 16 bits. If, however, only eight bits are available also for the representation of the estimate, the 16-bit estimate y has to be replaced by an 8-bit estimate y' , and therefore the other eight bits will have to be truncated. Since all 16 bits may be carrying information, it will be obvious to keep the eight most significant bits and truncate the eight least significant bits, as it is shown in figure 2.

However, by low signal levels the most significant bits of the received signal r may have the value "0", and the same may be the case for the conjugate \hat{h}^* . In figure 3 an example is shown, in which the three first bits of r and the two first bits of \hat{h}^* have the value "0". As a result, also the five first bits of the estimate y will have the value "0". If y' is still taken as the eight most significant bits of y , as shown in figure 3, much information will be lost, since only three information carrying bits are left in y' .

Instead, it would be more expedient to leave out the five "0"-bits and select the following eight bits for y' , as it is illustrated in figure 4. The same result is achieved if the value y with the leading zeros is shifted five bits to the left, which corresponds to multiplying y by a scaling factor 2^5 , and y' is then again taken as the eight most significant bits of the scaled value y_{sc} . This is illustrated in figure 5, and a corresponding circuit is shown in figure 6, in which the signal y is scaled in the scaling circuit 8, and a number of bits are truncated from the scaled value y_{sc} in the truncating circuit 7. An overflow check

and a no-overflow check may be applied to the scaled value y_{sc} to ensure that the value is shifted the optimal number of bits to the left.

5 The present invention relates to the selection of an appropriate scaling factor to be used in the scaling circuit 8. If a fixed factor is used, there will sometimes be overflow, and sometimes there will still be leading zeros. Adaptive algorithms exist which are able to continuously update the scaling factor based on the input to the circuit, but these algorithms typically require more computational power than is available in portable terminals.

10

As mentioned, the estimate y' , i.e. the estimated coded data symbol, is the input to a channel decoder 6, which as examples could be a turbo decoder or a convolutional decoder. The performance of this decoder will depend on the selected scaling factor in the scaling circuit 8. The performance may be measured as an achieved block error rate (BLER) as a function of the signal-to-interference ratio (SIR) of the received radio signal. Figure 7 shows an example, where two different scaling factors, factor I and factor II, are used. The signal-to-interference ratio may be changed by changing the signal level of the signal transmitted from the remote end of the transmission link, and thus figure 7 shows as an example that if scaling factor I is used in combination with this decoder, a signal-to-interference ratio of $-8,3$ dB is needed to provide a block error rate of 10^{-2} . If, however, scaling factor II had been used, a signal-to-interference ratio of -9 dB would have been sufficient to achieve the same block error rate. On the other hand, if a block error rate of 10^{-4} is required, scaling factor I is the only usable scaling factor, because with factor II block error rates below approximately 10^{-3} cannot be achieved. If, for instance, scaling factor I is 2^2 , corresponding to shifting two bits to the left, and scaling factor II is 2^4 , corresponding to shifting four bits to the left, factor II will result in overflow when the signal level reaches a certain level, and that is the reason that prevents the low block error rates from being achieved with this factor.

15
20
25
30

In systems according to 3GPP the network actually provides the receiver with a target value for the block error rate (target BLER), and thus according to the invention this target BLER value is used to select the scaling factor of the scaling circuit 8.

5

In a preferred embodiment a table with corresponding values of target BLER values and scaling factors is used. An example is shown in figure 8. It is seen that scaling factor I (2^2) is selected for target BLER values $\leq 10^{-3}$, while scaling factor II (2^4) is selected for target BLER values $> 10^{-3}$.

10

Another example is shown in figures 9 and 10, in which three different scaling factors are used. In this case, scaling factor I (2^2) is selected for target BLER values $\leq 10^{-4}$, while scaling factor II (2^3) is selected for target BLER values in the range $10^{-4} - 10^{-3}$, and scaling factor III (2^4) is selected for target BLER values $> 10^{-3}$.

15

By using the information about the target BLER value and a look-up table the scaling factor can be optimized for several target BLER values compared to the situation where only one scaling factor is used. The better performance is achieved with the use of only slightly higher amount of computational resources. Thus the suggested solution requires much less complexity than the use of adaptive algorithms, which continuously estimate e.g. the signal-to-interference ratio or the actual block error rate.

20

25 In the above description the information about the target BLER value is used for selecting a scaling factor. Instead of using a scaling factor, the relevant bits may also be selected directly as it was illustrated in figure 4, and in that case the information about the target BLER value defines the position of the selected bits. Further, truncation is just one of several possible rounding methods, and of course the idea of the invention can be used with other
30 rounding methods as well.

Although a preferred embodiment of the present invention has been described and shown, the invention is not restricted to it, but may also be embodied in other ways within the scope of the subject-matter defined in the following claims.

P a t e n t c l a i m s : ---

- 5 1. A method of receiving coded digital data symbols sent from a transmitter through a transmission channel of a communications network, the method comprising the steps of:

 - calculating an estimate (y) of a sent data symbol, said estimate being represented by a first number (a+b) of bits;
 - selecting from said calculated estimate a second number (c) of bits,
 - 10 said second number (c) being lower than said first number (a+b), to achieve a rounded estimate (y') being represented by said second number (c) of bits; and
 - decoding the rounded estimate (y') to achieve a decoded data symbol,

15 c h a r a c t e r i z e d in that the method further comprises the steps of:

 - receiving from said network a target value for a block error rate of the transmission channel; and
 - selecting said second number of bits in dependence on said target block error rate value.

20
2. A method according to claim 1, c h a r a c t e r i z e d in that the step of selecting said second number of bits comprises the steps of:

 - multiplying said estimate (y) by a scaling factor; and
 - truncating a number of bits from said multiplied estimate (y_{sc}).

25
3. A method according to claim 2, c h a r a c t e r i z e d in that said scaling factor has the form 2^n , where n is an integer.
4. A method according to claim 2 or 3, c h a r a c t e r i z e d in

30 that the method further comprises the step of selecting said scaling factor from a stored table comprising corresponding values of said target block error rate and said scaling factor.

5. A method according to any one of claims 1 to 4, c h a r a c t e r -
i z e d in that said target block error rate value is the target BLER value
defined in the technical specifications of 3GPP (3rd Generation Partnership
Project).

5

6. A receiver for receiving coded digital data symbols sent from a transmitter
through a transmission channel of a communications network, the receiver
being arranged to:

- calculate an estimate (y) of a sent data symbol, said estimate being
10 represented by a first number (a+b) of bits;
- select from said calculated estimate a second number (c) of bits, said
second number (c) being lower than said first number (a+b), to
achieve a rounded estimate (y') being represented by said second
number (c) of bits; and
- 15 • decode the rounded estimate (y') to achieve a decoded data symbol,
c h a r a c t e r i z e d in that the receiver is further arranged to:
 - receive from said network a target value for a block error rate of the
transmission channel; and
 - select said second number of bits in dependence on said target block
20 error rate value.

7. A receiver according to claim 6, c h a r a c t e r i z e d in that
the receiver is further arranged to select said second number of bits by:

- multiplying said estimate (y) by a scaling factor; and
- 25 • truncating a number of bits from said multiplied estimate (y_{sc}).

8. A receiver according to claim 7, c h a r a c t e r i z e d in that
said scaling factor has the form 2^n , where n is an integer.

30 9. A receiver according to claim 7 or 8, c h a r a c t e r i z e d in
that the receiver comprises a stored table comprising corresponding values
of said target block error rate and said scaling factor, from which table said
scaling factor can be selected.

10. A receiver according to any one of claims 6 to 9, c h a r a c -
t e r i z e d in that said target block error rate value is the target BLER
value defined in the technical specifications of 3GPP (3rd Generation Part-
5 nership Project).

Selecting a rounded estimate in a receiver of coded digital data symbols

ABSTRACT

Coded digital data symbols sent from a transmitter through a transmission channel of a communications network are received in a receiver. An estimate, represented by a first number of bits, of a sent data symbol is calculated, and a second number of bits, lower than the first number, is selected from the estimate to achieve a rounded estimate represented by the second number of bits. The rounded estimate is decoded to achieve a decoded data symbol. A target value for a block error rate of the transmission channel is received from the network; and the second number of bits is selected in dependence on the target block error rate value. Thus an optimal rounded estimate is provided in most situations, and the method can be performed with the limited computational resources of a terminal.

Fig. 7 should be published.




Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5




Fig. 6




Fig. 7

Target BLER	Scaling Factor
$\leq 10^{-3}$	2^2 (Factor I)
$> 10^{-3}$	2^4 (Factor II)

Fig. 8




Fig. 9

Target BLER	Scaling Factor
$\leq 10^{-4}$	2^2 (Factor I)
$10^{-4} - 10^{-3}$	2^3 (Factor II)
$> 10^{-3}$	2^4 (Factor III)

Fig. 10